



07/12/00

UTILITY PATENT APPLICATION TRANSMITTAL UNDER 37 C.F.R. §1.53(b)

ASSISTANT COMMISSIONER FOR PATENTS

Box PATENT APPLICATION

Washington D.C. 20231

Case Docket No.: P-106

Sir:

Transmitted herewith for filing is the patent application of

INVENTOR OR APPLICATION IDENTIFIER: Seung-Hwan BAE

FOR: DUPLICATING PROCESSORS AND METHOD FOR CONTROLLING ANOMALOUS DUAL STATE
THEREOF

Enclosed are:

1. ☒ 20 pages of specification, claims, abstract
2. ☒ 5 sheets of FORMAL drawing.
3. ☒ 2 pages of newly executed Declaration & Power of Attorney (original).
4. ☒ Priority Claimed to Korean Appln. No. 28544/1999, whose entire disclosure is incorporated herein by reference.
5. ☐ Small Entity Statement.
6. ☐ Information Disclosure Statement, Form PTO-1449 and reference.
7. ☒ Assignment Papers for LG Information & Communications, Ltd. (cover sheet, assignment & assignment fee).
8. ☒ Certified copy of Korean Patent Application No. 28544/1999 filed July 14, 1999.
9. ☒ Two (2) return postcards.
☒ Stamp & Return with Courier.
☒ Prepaid Postcard-Stamped Filing Date & Returned with Unofficial Serial Number.
10. ☒ Authorization under 37 C.F.R. §1.136(a)(3).
11. ☐ Other:

jc542 U.S. PTO
09/614719
07/12/00

CLAIMS AS FILED

For	No. Filed		No. Extra	Rate	Fee
Total Claims	20	- 20	0	X \$18.00	\$0.00
Indep. Claims	3	- 3	0	X \$78.00	\$0.00
Multiple Dependent Claims (If applicable)				X \$260.00	\$0.00
				BASIC FEE	\$690.00
				TOTAL FILING FEE	\$690.00

- ☐ This is a Continuation-in-part (CIP) of prior application No: _____ filed _____. Incorporation By Reference-The entire disclosure of the prior application is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.
- ☐ Amend the specification by inserting before the first line the sentence:
--This application is a continuation-in-part of Application Serial No. _____ filed _____.--
- ☒ A check in the amount of \$690.00 (Check #8975) is attached.
- ☐ Please charge my Deposit Account No. 16-0607 in the amount of \$____. A duplicate copy of this sheet is enclosed.
- ☒ The Commissioner is hereby authorized to charge payment of the following fees associated with this communication or credit any overpayment to Deposit Account No. 16-0607. A duplicate copy is enclosed.
☒ Any additional filing fees required under 37 C.F.R. 1.16.
- ☒ The Commissioner is hereby authorized to charge payment of following fees during the pendency of this application or credit any overpayment to Deposit Account No. 16-0607. A duplicate copy of this sheet is enclosed.
☒ Any patent application processing fees under 37 C.F.R. 1.17.
☒ Any filing fees under 37 C.F.R. 1.16 for presentation of extra claims.

FLESHNER & KIM, LLP

Daniel Y.J. Kim
Registration No. 36,186

Correspondence Address Below:

P.O. Box 221200

Chantilly, VA 20153-1200

(703) 502-9440 DYK/kam

Date: July 12, 2000

DUPLICATING PROCESSORS AND METHOD FOR CONTROLLING ANOMALOUS DUAL STATE THEREOF

BACKGROUND OF THE INVENTION

5

1. Field of the Invention

The present invention relates to a communication system, and more particularly, to duplicating processors and a method for controlling anomalous dual state of the duplicated processors.

10

2. Description of the Background Art

15

Generally, in order to improve reliability and stability in service of a communication system, a hardware path that transmits data is implemented by duplicating(active mode/standby mode), of which an active path is set at an initial stage through which data is transmitted, and if a disturbance occurs in the active path, a separately provided standby path is automatically switched to successively operated.

20

However, a communication system having the tightly coupled active/standby scheme that is physically constructed by hardware has disadvantages. The hardware architecture should be redesigned and a new operating system on it should be required. In addition, expense and time are required too much to develop a new programming language.

25

In an effort to overcome the drawbacks, as shown in Figure 1, recent communication systems are established in that two processors 10 and 20 are loosely coupled through a network and heartbeat signals (HB_Tx/HB_Rx) that are

periodically transmitted and received between the processors are used to process the duplication state by software.

For this purpose, the processors 10 and 20 respectively include blocks for performing the duplication function.

5 With reference to Figure 2, the processor A 10 includes an incoming heartbeat processing block 11, a duplication FSM(Finite State Machine) processing block 12 and an outgoing heartbeat processing block 13. The processor B 20 has the same flow.

10 The incoming heartbeat processing block 11 receives a heartbeat (HB_Rx) from the processor B 20, that is, the other processor (twin) and transfers state information of the twin 20 to the duplication FSM processing block 12. If no heartbeat is received from the twin 20 within a predetermined time, it reports a network disturbance or a twin down to the duplication FSM processing block 12.

15 The duplication FSM processing block 12 is charged with a corresponding state transition function according to the state information of the twin 20 included in the heartbeat (HB_Rx) or a switching event captured by the incoming heartbeat processing block 11, so that it applies the state information of itself corresponding to each state to the outgoing heartbeat processing block 13 or renders the outgoing heartbeat processing block 13 to transmit a heartbeat signal immediately
20 in every state transition.

The outgoing heartbeat processing block 13 transmits the heartbeat (HB_Tx) to the twin 20 immediately or periodically according to the state information applied from the duplication FSM processing block 12.

25 Figure 3 illustrates a state transition of the duplication FSM block in accordance with a conventional art.

The state transition process in accordance with the conventional art will now be described with reference to Figure 3.

Each state transition is made by a twin state event such as 'Twin START', 'Twin ACTIVE' or 'Twin TIMEOUT' or by an external event such as 'Shutdown Command', 'Restart' or 'Manual Switchover'.

First, as the FSM is driven and all blocks on overall system are completely initialized, the duplication FSM allows the "INITIAL" state to transit to the "START" state.

And, the self processor confirms a state of the twin, and If the twin has been also started, the self processor is transited to 'NEGOTIATION' state to determine which side gives services as an active one. In the 'NEGOTIATION' state, it was predetermined that which of either one of two processors is to be active.

For example, if the processor A is set as an active processor, each processor confirms whether itself is the processor A in the 'NEGOTIATION' state. If either processor confirms itself as the processor A, it is transited to 'ACTIVE' state, or otherwise, it is transited to 'STANDBY' state.

Meanwhile, when the processor A is in 'ACTIVE' state, if the twin is in 'ACTIVE' state or if 'Manual switchover' occurs, the processor A is transited to 'STANDBY' state. And, if a network error or a disturbance occurs, the processor A is transited to 'PENDING STANDBY' state.

When the processor A is in 'PENDING STANDBY' state, it confirms a state of twin, and if the twin that is, the processor B is in 'ACTIVE' state, the processor A is transited to a 'SYNCH' state and then transited to 'STANDBY' state when synchronization is completed, while if the processor B is in 'STANDBY' state,

the processor A is transited to 'ACTIVE' state.

Meanwhile, in case that the 'Manual switchover' occurs or the processor B is 'Timeout' before synchronization is completed, the processor A is transited to 'ACTIVE' state.

5 When the processor A is in 'STANDBY' state, if 'Manual switchover' occurs, the processor A is transited to 'ACTIVE' state. In case that the twin(processor B) is in 'STANDBY' state, the processor A is transited to 'PENDING ACTIVE' state and confirms a state of the twin. If the processor B is in 'STANDBY' state, the processor A is transited to 'ACTIVE' state, or otherwise, it is transited to
10 'STANDBY' state.

However, in case that the duplication is implemented by software through network as described above, there is a possibility that the network disturbance occurs or the network resources such as a cable or a hub are defected or disturbed. Then, each processor would judge that the twin has gone down,
15 resulting in that both processors become active, which makes a confusion for external network elements/participants that mutually works with the processors, causing a problem failing to perform a normal operation.

In addition, even though the disturbance is restored, at just the time of restoration of the disturbance, it may fall to an anomalous dual state, though it
20 happens at few random.

Moreover, if the two processors become all 'ACTIVE' state, since they recognize the other party as being in 'ACTIVE' state based on the received heartbeat, itself is accordingly transited to the 'STANDBY' state immediately. Meanwhile, in case that the two processors become all in 'STANDBY' state, since
25 they recognize the other party as being in 'STANDBY' state based on the received

heartbeat, itself is accordingly transited to the 'PENDING ACTIVE' state immediately. The difficulty is met in case that the twin may do the same action at the time.

If the twin is not the 'PENDING ACTIVE' nor 'ACTIVE', itself is transited to the 'ACTIVE' state. In this respect, normally, there is time differences to an extent in receiving the heartbeat, so that it may be prevented from falling into a double active state out of the 'PENDING ACTIVE' state.

That is, at this stage, differences are made in the receiving intervals of the heartbeat, so that the party that first reaches the 'PENING ACTIVE' state is transited to an active state and the party that reaches later is transited to the 'STANDBY' state, thereby maintaining a normal state.

However, if the heartbeat is transmitted or received at the accurately same time, an anomalous dual active/standby state is inevitably caused. Then, a state fluctuation phenomenon may occur that transition is made to the dual active/standby state, failing to perform a normal duplication.

SUMMARY OF THE INVENTION

Therefore, an object of the present invention is to provide duplicating processors and a method for controlling anomalous dual state in which seeds for generating random numbers are differently allocated when each processor is initialized to generate the different random number and transmission period of a heartbeat is continuously changed by using the random number, thereby avoiding an anomalous dual state.

Another object of the present invention is to provide a method for

controlling duplicating processors which is capable of quickly restoring an anomalous dual state even though it occurs due to an abnormality on a network or on a system.

To achieve these and other advantages and in accordance with the purpose of the present invention, as embodied and broadly described herein, there is provided a method for controlling anomalous dual state of duplicated processors for a duplication system having a first and a second processors that are connected to each other through network, including the steps of: transmitting its own state information of either the first or the second processor to mutually another processor (twin) by using different transmission period to each other; receiving the heartbeat applied from the other processor and recognizing state information of the twin; and performing duplication states according to the state information of the twin.

In order to achieve the above objects, there is also provided duplicating processors in a fault-tolerant system having a first and a second processors that are mutually connected through a network, of which each processor has an outgoing heartbeat processing block for transmitting a heartbeat including its own state information to the other processor (twin) by using a different period to each other; an incoming heartbeat processing block for receiving the heartbeat from the other processor and recognizing the state information of the twin; and a duplication FSM processing block for performing duplication states processing according to the state information of the twin.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are included to provide a further
5 understanding of the invention and are incorporated in and constitute a part of this
specification, illustrate embodiments of the invention and together with the
description serve to explain the principles of the invention.

In the drawings:

Figure 1 is a block diagram illustrating a simple duplication architecture of
10 a system through network in accordance with a conventional art and the present
invention;

Figure 2 is a block diagram illustrating blocks for performing duplication
process in each processor in accordance with the conventional art and the present
invention;

15 Figure 3 illustrates a duplication FSM diagram in a duplication FSM
processing block in accordance with the conventional art and the present
invention;

Figure 4 is a flow chart of a process for transmitting a heartbeat of a
outgoing heartbeat processing block in accordance with the present invention; and

20 Figure 5 is a flow chart of a process for receiving heartbeat of an incoming
heartbeat processing block in accordance with the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made in detail to the preferred embodiments of the present invention, examples of which are illustrated in the accompanying drawings.

The construction of a basic duplicated system for executing the present invention is the same as those of Figures 1 and 2 and its duplication state transition process is the same as that of Figure 3, for which, thus, descriptions are omitted.

Figure 4 is a flow chart of a process for transmitting a heartbeat of an outgoing heartbeat processing block in accordance with the present invention; and Figure 5 is a flow chart of a process for receiving heartbeat of an incoming heartbeat processing block in accordance with the present invention.

The process for controlling duplication state of a processor in accordance with the present invention will now be described with reference to the accompanying drawings.

The duplicated processors A and B 10 and 20 use heartbeats (HB_Tx/HB_Rx) that are mutually transmitted and received therebetween to inform the twin of its own state information and monitor the state of the twin. In this respect, in order to produce a continuous difference for the heartbeat transmission intervals, random number periods are generated.

For this purpose, first, when each processor 10 and 20 is initialized, seeds for different random numbers are allocated to generate random numbers, and the time tuned by a generated random number is used as a transmission period of the heartbeat of the outgoing heartbeat processing block 13.

In order to generate a suitable tuned period, an average transmission time 'a' through a link between the processors A and B 10 and 20, an average heartbeat processing time of processors 'b' and a state transition time 'c' should be considered.

5 Before each processor receives nth heartbeat from the twin, each processor should be already completed processing of the n-1th heartbeat and only one heartbeat message at its maximum should exist in the transmission path of a corresponding heartbeat at the point of a specific time.

Accordingly, a fixed-period heartbeat transmission period 'x' should satisfy
10 the following formula: $0 < (2a+b+c) < x$. And, assuming that a heartbeat transmission period to be changed is 'p', the variable period and a maximum tolerance of a period change, that is, $|p-x|$ is ' Δp ', since $(2a+b+c)$ becomes the maximum value that can be included in ' Δp ', $(2a+b+c) < x/2$. Accordingly, $(2a+b+c)$ should satisfy the following formula: $0 < 2(2a+b+c) < x$.

15 In this respect, if the change in the heartbeat is desired to be in a predetermined suitable range, that is, in the range from $(x-\Delta p)$ to $(x+\Delta p)$, the current heartbeat should be within the next heartbeat transmission time. Besides, in consideration of the time required for receiving and processing, the transmission period 'p' to be changed should satisfy the following formula: $x-(2a+b+c) < p < x+(2a+b+c)$.
20

Accordingly, $-(2a+b+c) < p-x < (2a+b+c)$, that is, $|p-x| < (2a+b+c)$. In this respect, on the basis of the above definition, since $\Delta p = |p-x|$, $\Delta p < (2a+b+c)$.

The above formula can be extended to the following formula: $(2a+b+c) < x - (2a+b+c) < p < 3(2a+b+c) < x + (2a+b+c)$.

25 Therefore, the maximum tolerance of the period change ' Δp ' should be

within $(2a+b+c)$, and the transmission period 'p' to which the change is actually applied should be continuously changed in the range from $x-(2a+b+c)$ to $x+(2a+b+c)$.

The random generation process will now be described according to an embodiment based on an experiment.

Values 'a', 'b' and 'c' may be varied depending on the system specification and a network environment. In this case, they can be set by correcting a configuration by tuning when a system is set up.

In the experiment, a value obtained by averaging values simply measured for 10 times on the basis of a TX1A system was used. For the simplicity, we used a configuration file as the way of storing measured values.

Test system: SPARC 10 dual CPU Unix Processor Board

x: the fixed heartbeat period : 500 ms

a: an average transmission time : 14.7 ms

b: an average heartbeat processing time : 1.2 ms

c: an average a state transition time : 2.8 ms

$(2a+b+c) = 33.4 \text{ ms} > |p-x|$

In a configuration file,

AD.HB.VAR_LIMIT_SEC = 0

AD.HB.VAR_LIMIT_USEC = 33400

AD.HB.PERIOD_SEC = 0

AD.HB.PERIOD_USEC = 500000

...

variable seed : a random seed

```

variable hbVarLimit : a limit that heartbeat period can vary
variable x : the fixed heartbeat period
variable prevrange : the old varied range within the limit
variable newrange : the new acceptable range to be varied at a new
5 period within the limit
variable p : the heartbeat period to be newly changed
*** the time unit of the above all period related variables is micro second.

/* pseudo code for initialization of a system */
10 concern the unique processor id as the random seed and assign it to a
variable seed ;

/* seed = processor_id ; */
initialize the random number generator with the seed value ;
/* randomize(seed) ; */
15 read an environment variable VAT_LIMIT_USEC and store it to a variable
hbVarLimit

/* hbVarLimit = get_parameter(HB.VAR_LIMIT_USEC) ; */
read an environment variable PERIOD_USEC and store it to a variable x ;
/* x = get_parameter(HB.PERIOD_USEC) ; */
20 initialize a variable prevrange ;

/* prevrange = 0 */
...

/* pseudo code in outgoing heartbeat processing block */
25 {

```

choose a random number in the range of hbVarLimit and assign it to a variable newrange;

`/* newrange = random() % hbVarLimit + 1; 1~33400 */`

determine the sign of the newrange ;

5 `/* newrange *= (random() % 2 ? 1: -1) ; by dividing the value by 2, if a remainder is 1, it gets +value, while if the remainder is 0, it gets -value */`

assign the newly modified period to a variable x ;

`/* p = x -prevrange + newrange ; a previous modified value is corrected to give a change in the fixed period */`

10 cancel the previous timer

`/* cancel_time (outgoingTimer_) ; a previous timer is finished */`

schedule a new timer to execute sendHeartbeatFunction block after p micro seconds

15 `/* outgoingTimer = schedule_time (thisObject, sendHeartbeatFunction, 0, p ; sec = 0, usec = p */`

store the newrange as a prevrange

`/* prevrange = newrange ; */`

}

20 The heartbeat transmission process of the outgoing heartbeat processing block 13 in which the heartbeat is transmitted by generating the random numbers will now be described with reference to Figure 4.

First, in order to transmit state information applied from the duplication FSM processing block 12 to the twin, the random numbers are generated
25 according to the above-stated process and used to generate the transmission

period of a heartbeat (S11).

And then, a timer is scheduled and started(S12). As a transmission time determined at step S11 lapses (S15), a heartbeat carrying self state information is transmitted to the twin (S16), and then it returns to the step S11.

5 When the outgoing heartbeat processing block 13 transmits the heartbeat through the above process, the incoming heartbeat processing block of the other processor receives the heartbeat and informs its own duplication FSM processing block of the state information of the twin, as shown in Figure 5.

10 First, the incoming heartbeat processing block schedules and starts the timer (S21) and waits for the heartbeat to be transmitted from the twin for a predetermined time. In this respect, the predetermined time is determined as a sufficient value greater than the maximum value of the heartbeat transmission period.

15 When the incoming heartbeat processing block receives the heartbeat from the twin within a predetermined time (S22), it stops the timer (S24) and transmits the received state information of the twin to the duplication FSM processing block (S25), and goes back to step S21.

20 Meanwhile, if no heartbeat is transmitted from the twin until a predetermined time lapses, the incoming heartbeat processing block judges that the twin has been down, and transmits information related to the down to the duplication FSM block (S25).

25 As so far described, according to the method for controlling duplicated processors of the present invention, when the two processors start, seeds for the random number are differently allocated to generate different random numbers, and the heartbeat transmission period is continuously changed by using the

random numbers to differentiate the transmission and receiving time of the heartbeat between the two processors. Therefore, an anomalous dual state transition, that is, a state fluctuation phenomenon that dual ACTIVE and dual STANDBY are repeatedly performed that may occur in concurrently receiving the heartbeat by two processors, can be prevented from occurring.

In addition, at the time when a network-related disturbance is restored, since each transmission period of the two processors is differently changed to each other, so that a prompt restoration can be ensured.

As the present invention may be embodied in several forms without departing from the spirit or essential characteristics thereof, it should also be understood that the above-described embodiments are not limited by any of the details of the foregoing description, unless otherwise specified, but rather should be construed broadly within its spirit and scope as defined in the appended claims, and therefore all changes and modifications that fall within the meets and bounds of the claims, or equivalence of such meets and bounds are therefore intended to be embraced by the appended claims.

What is claimed is:

1. A method for controlling anomalous dual state of duplicated processors for a fault-tolerant system having a first and a second processors that
5 are connected to each other through network, comprising:

a first step of transmitting its own state information of either the first or the second processor to mutually another processor (twin) by using different transmission period to each other;

a second step of receiving the heartbeat applied from the other processor
10 and recognizing state information of the twin; and

a third step of performing duplication states according to the state information of the twin.

2. The method according to claim 1, wherein the first step includes
15 sub-steps of:

generating a heartbeat transmission period by using random numbers;

scheduling and starting a timer on the basis of the generated random period; and

transmitting a heartbeat to the other processor after time tuned by a
20 generated random number lapses.

3. The method according to claim 2, wherein when the random period is generated, in order for the first and the second processors to have the different tuned period to each other, different seeds for random numbers are
25 allocated to each other, when a system is initialized.

4. The method according to claim 2, further comprising a step of:
stopping the timer in case that state change occurs before the period tuned by a
generated random number lapses, and immediately transmitting a corresponding
5 heartbeat to the other processor.

5. The method according to claim 2, wherein the period tuned by a
generated random number of the heartbeat is determined so that only one
heartbeat message at its maximum exists in a corresponding heartbeat
10 transmission path at the point of a specific time.

6. The method according to claim 4, wherein the period tuned by a
generated random number of the heartbeat is determined by a value changed
from a fixed heartbeat transmission period in consideration of a corresponding
15 heartbeat transmission time, a heartbeat processing time and a state transition
time.

7. The method according to claim 6, wherein assuming that a fixed
heartbeat transmission period is 'x', the heartbeat transmission time is 'a', the
20 heartbeat processing time is 'b' and the state transition time is 'c', the variable
heartbeat transmission period is determined in the range from $x-(2a+b+c)$ to
 $x+(2a+b+c)$.

8. The method according to claim 1, wherein the second step
25 comprising the sub-steps of:

waiting for receiving the heartbeat for a predetermined time;
recognizing a receipt of the heartbeat; and
judging that the twin has gone down if no heartbeat is received within a predetermined time.

5

9. The method according to claim 8, wherein the predetermined time refers to a value sufficiently greater than the maximum value that can be held by the period tuned by a generated random number for a heartbeat transmission.

10

10. Duplicated processors on a fault-tolerant system having a first and a second processors that are mutually connected through a network, wherein each processor comprising:

15

an outgoing heartbeat processing block for transmitting a heartbeat including its own state information to the other processor (twin) by using a different transmission period to each other;

an incoming heartbeat processing block for receiving the heartbeat from the other processor and recognizing the state information of the twin; and

a duplication FSM processing block for performing duplication states processing according to the state information of the twin.

20

11. The processor according to claim 10, wherein the outgoing heartbeat processing block includes a random number generator to continuously change the transmission period of the heartbeat.

25

12. The processor according to claim 11, wherein when the random

period is generated, in order for the first and the second processors to have the different turned period to each other, different seeds for random numbers are allocated to each other, when a system is initialized.

5 13. The processor according to claim 11, wherein the period turned by a generated random number of the heartbeat is determined so that only one heartbeat message at its maximum exists in a corresponding heartbeat transmission path at a specific time point.

10 14. The processor according to claim 11, wherein the period turned by a generated random number of the heartbeat is determined by a value changed from a fixed heartbeat transmission period in consideration of a corresponding heartbeat transmission time, a heartbeat processing time and a state transition time.

15 15. The processor according to claim 14, wherein assuming that a fixed heartbeat transmission period is 'x', the heartbeat transmission time is 'a', the heartbeat processing time is 'b' and the state transition time is 'c', the variable heartbeat transmission period is determined in the range from $x-(2a+b+c)$ to
20 $x+(2a+b+c)$.

25 16. A method for transmitting a heartbeat of duplicated processors on a fault-tolerant system having a first and a second processors that are connected through network, in which the first and the second processors use different transmission periods to transmit heartbeats.

17. The method according to claim 16, wherein in order to generate different transmission periods to each other, different seeds for random numbers are allocated to the first and the second processors to thereby generate random
5 numbers, by which a heartbeat transmission period is generated.

18. The method according to claim 17, wherein the period turned by a generated random number of the heartbeat is determined so that only one heartbeat message at its maximum exists in a corresponding heartbeat
10 transmission path at the point of a specific time.

19. The method according to claim 17, wherein the period turned by a generated random number of the heartbeat is determined by a value changed from a fixed heartbeat transmission period in consideration of a corresponding
15 heartbeat transmission time, a heartbeat processing time and a state transition time.

20. The method according to claim 19, wherein assuming that a fixed heartbeat transmission period is 'x', the heartbeat transmission time is 'a', the
20 heartbeat processing time is 'b' and the state transition time is 'c', the variable heartbeat transmission period of the heartbeat is determined in the range from $x - (2a+b+c)$ to $x + (2a+b+c)$.

ABSTRACT OF THE DISCLOSURE

A method for controlling anomalous dual state of duplicated processors for a fault-tolerant system having a first and a second processors that are connected to each other through network, comprising: a first step of transmitting its own state information of either the first or the second processor to mutually another processor (twin) by using different transmission period to each other; a second step of receiving the heartbeat applied from the other processor and recognizing state information of the twin; and a third step of performing duplication states according to the state information of the twin. By doing that, when the two processors start, the seeds for random numbers are differently allocated to generate different random numbers, and the heartbeat transmission period is continuously changed by using the random numbers to differentiate the transmission and receiving time of the heartbeat between the two processors. Therefore, an anomalous dual state transition, that is, a state fluctuation phenomenon that dual ACTIVE and dual STANDBY are repeatedly performed that may occur in concurrently receiving the heartbeat by two processors, can be prevented from occurring.

FIG. 1




FIG. 2




FIG. 3





FIG. 4



002149.071200

Docket No.:

DECLARATION AND POWER OF ATTORNEY

As a below named inventor, I hereby declare that:

My residence, post office and citizenship are as stated below next to my name,

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter claimed and for which a patent is sought on the invention entitled DUPLICATING

PROCESSORS AND METHOD FOR CONTROLLING ANOMALOUS DUAL STATE THEREOF, the specification of which

☒ is attached hereto ☐ was filed on _____ as Application Serial No. _____ and was amended on _____ (if applicable)

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is known to me to be material to patentability in accordance with Title 37, Code of Federal Regulations, Section 1.56(a).

I hereby claim foreign priority benefits under 35 U.S.C. 119(a)-(d) or 365(b) of any foreign application(s) for patent or inventor's certificate, or 365(a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below, by checking the box, any foreign application for patent or inventor's certificate, or of any PCT international application having a filing date before that of the application on which priority is claimed.

<u>Prior Foreign Application(s):</u> <u>Number</u>	<u>Country</u>	<u>Foreign Filing Date</u> <u>Month/Day/Year</u>
28544/1999	Korea	07/14/1999

I hereby claim the benefit under 35 U.S.C. 119(e) of any United States provisional application(s) listed below.

<u>Application Number(s)</u>	<u>Filing Date(Month/Day/Year)</u>

I hereby claim the benefit under 35 U.S.C. 120 of any United States application(s), or 365(c) of any PCT international application Designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT international application in the manner provided by the first paragraph of 35 U.S.C. 112, I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.

<u>Prior U. S. Application</u> <u>or PCT Patent Number</u>	<u>Filing Date(Month/Day/Year)</u>	<u>Parent Patent Number(if application)</u>

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

FLESHNER & KIM
P.O. Box 221200
Chantilly, Virginia 20153-1200

Date: Jul 107/2000

Post Office Address: Sigma II Officetel A-228, 18, Kumi-Dong, Bundang-Ku, Sungnam,
Kyungki-Do, Korea

[illegible]